

BRUSHLESS MOTORS
NX630EAV
ELECTRONIC DRIVE (1)
DIGIVEX 4/8

(230 V)

(400 V)




Torque at low speed	M_o	Nm	12		
Permanent current at low speed	I_o	A_{rms}	2.62		
Peak torque	M_p	Nm	40		
Current for the peak torque	I_p	A_{rms}	10.5		
Back emf constant at 1000 rpm (25°C)*	K_e	V_{rms}	277		
Torque sensitivity	K_t	Nm/A_{rms}	4.57		
Winding resistance (25°C)*	R_b	Ω	9.19		
Winding inductance*	L	mH	99.6		
Rotor inertia	J	$kgm^2 \times 10^{-5}$	147		
Thermal time constant	T_{th}	min	33		
Motor mass	M	kg	8.9		
Voltage of the mains	UR1 UR2 UR3	V_{rms}	230	400	480
Rated speed	Nn1 Nn2 Nn3	rpm	750	1350	1500
Rated torque	Mn1 Mn2 Mn3	Nm	11.39	10.83	10.68
Rated current	In1 In2 In3	A_{rms}	2.51	2.40	2.37
Rated power	Pn1 Pn2 Pn3	W	890	1530	1680

All data are given in typical values under standard conditions

* Phase to phase

(1) Please check the availability of this drive with 480 V

Voltages and currents are given in rms values



Characteristics are given for an optimal drive of the motor

FICHE-009

Création: 16 nov 2000

Edition: 10/févr/2005

NX630EAV