



**RESOLVEUR**

CARACTERISTIQUES a 5 KHz  
Tension d'entree.....:7 Veff  
Courant d'entree.....:70 mA Maxi  
Precision.....:±10° Maxi  
Rapport de transf.....:0.5  
Déphasage.....:20° Maxi

**FREIN**

Tension d'alimentation : 24 V $\pm$ 10%  
Couple statique

	HXA30V	HXA40V-HXA50V-HXA60V
20°C	150 Nm	350 Nm
100°C	130 Nm	310 Nm

**TABLEAU DE COTES**

	HXA30V	HXA40V	HXA50V	HXA60V
L Maxi	582	660	702	702
A	265	343	385	385
B	216	294	336	336
C	153	153	153	153
D	111	111	111	111
E	271	349	391	391

Plan valable pour : R9300

Masse : * kg	Jeu axial arbre :	Dessine	17/02/99	DL	Vise	Service	FEDX	Echelle	1/5	<b>PARVEX</b> 8 Avenue du Lac. BP249 21007 DIJON CEDEX	<b>HXA00V + FREIN</b> <b>ENCOMBREMENT</b>	Format	A3	Famille :	ENC
Ce dessin, propriété exclusive de notre société est strictement confidentiel. Il ne peut être communiqué, copié ou reproduit sans son autorisation écrite.	* sous * N	Modifications										Folio	1	<b>344099E9300</b>	